



## Cabinet lock

### KR-SK80-G

#### CABINET LOCK

The KR-SK80-G cabinet lock is a fingerprint device, equipped with an extremely sensitive fingerprint reader, an emergency power supply connector and an alarm informing that the voltage is too low.

#### MAIN PRODUCT FEATURES

- ⊕ Various working modes available (public mode, private mode etc), suit for different application
- ⊕ Low voltage alarm: if voltage is lower than 4.5V, lock will prompt with sound and light on every opening. And it can't be locked when voltage is lower than 4V
- ⊕ Micro USB connector/3.5mm socket for emergency power supply
- ⊕ Capacitive fingerprint scanner, high sensitive
- ⊕ Can store 20 fingerprints
- ⊕ Two ways for power supply: 4\*AAA battery & 12V DC



## TECHNICAL DATA

Model	KR-SK80-G
Material	ABS
Dimensions	80*80*27mm
Power supply	6V(4*1.5V AAA batteries)
Warning voltage	4,5V
Power lock	>4V
Mechanism of action	Motor/servo
Static power consumption	70uA
Dynamic power consumption	200mA
Unlocking	Fingerprint
Number of unlocks	500 000times
Reaction time	Less than 500ms
Working temperature	-20°C~65°C
Working humidity	10% ~ 90%RH
Certifications	CE; ISO9001; RoHS ;IAF,FCC